

# KVM Switches

## 2-Port Compact USB KVM Switch w/Audio and Cables



### Model #: B004-VUA2-K-R

- ▶ Fast, easy switching via keyboard hot keys, push buttons or software (not required)
- ▶ PC and Mac compatible
- ▶ Allows sharing of audio components between systems
- ▶ Compact design saves desk space
- ▶ No AC adapter required
- ▶ 2 cable kits included

## DESCRIPTION

The B004-VUA2-K-R is a 2-port Compact USB KVM Switch with optional audio and microphone switching function. It allows you to access, control, boot and reboot two USB-enabled computers from a single console (keyboard, monitor and mouse). The independent audio/mic switching function allows an uninterrupted audio experience - you can continue listening to audio even when you switch to the other computer.

It includes innovative, easy-to-use KVM Switcher Software for Windows® and Macintosh® platforms. A small client application facilitates your KVM switching operations such as computer selection, hot key sequence programming, auto-scanning, auto-scan delay time programming, independent or simultaneous audio/computer switching and more.

## KEY BUYING POINTS

- Fast, easy switching via keyboard hot keys, push buttons or software
- Plug-and-play setup - no software required
- Hot-swap capability allows easy addition or removal of computers without powering down the switch or other computers
- Speaker and microphone connections allow sharing of audio components between systems (standard 3.5 mm audio connections)
- Independent audio switching allows you to listen to audio from either computer, no matter which computer is active on your monitor
- Supports video resolutions up to 2048 x 1536 (standard 15-pin VGA connectors)
- Supports Microsoft® IntelliMouse® and the scrolling wheel on most mice
- Compact design saves desk space
- Does not require an AC adapter
- One Year Limited Warranty

## TYPICAL APPLICATIONS

- Use this KVM switch when accessing two USB-equipped computers with one monitor, keyboard and mouse.

## OPTIONS & ACCESSORIES

- 2-Port Compact PS/2 KVM Switch w/Audio and Cables ( Model # B004-VPA2-K-R )
- 2-Port DVI/USB KVM Switch w/Audio and Cables ( Model # B004-DUA2-K-R )

## SYSTEM REQUIREMENTS

- Console: VGA, SVGA or Multisync Monitor, USB Keyboard and USB Mouse
- Computers: VGA, SVGA or Multisync Monitor Port and USB Port

- Audio (Optional): Standard 3.5 mm Connectors

## PACKAGE INCLUDES

- Compact 2-port USB KVM Switch with Audio
- 2 KVM Cable Kits and 2 Audio Cables
- CD-ROM with Software
- Owner's Manual with Warranty Information

## COMPLETE SPECIFICATIONS

<b>Description</b>	2-Port Compact USB KVM Switch w/Audio and Cables
<b>Connector Number</b>	7
<b>Color</b>	Black
<b>Style</b>	Desktop
<b>Ports</b>	2
<b>Certifications</b>	FCC, CE, RoHS Compliant
<b>Console</b>	VGA, USB
<b>PC/Server</b>	VGA, USB
<b>Control</b>	Push Button, Hot Key, Software
<b>Max CPU</b>	2

### CONNECTORS

**KVM Connector 1**




USB A (Female)

**KVM Connector 2**



USB A (Female)

**Input Connector**



HD15 (Female)

**CPU Connector 1**



HD15 (Female)

**CPU Connector 2**



HD15 (Female)

*The policy of Tripp Lite is one of continuous improvement.  
Specifications are subject to change without notice.  
Therefore, your product may vary slightly from what is currently listed.*



**Tripp Lite World Headquarters**  
1111 W. 35th Street  
Chicago, IL 60609 USA

**Customer Support**  
(773) 869-1234

© 2007 Tripp Lite. All Rights Reserved.